

Pin and signal details

All logic levels are at 3.3V


PWR = input power, usually 3.5 .. 13V
(on JN USB: 3.5 .. 5V, or 4.2V with LiPo)

These pins of same color are all inter-connected:

PWR • +3V • GND • IRQ

DIO2, DIO3, and B1 support PWM

Ports



Port	Jee	Arduino	AVR	Jee	Arduino	AVR
P1	DIO1	digital 4	PD4	AIO1	analog 0	PC0
P2	DIO2	digital 5	PD5	AIO2	analog 1	PC1
P3	DIO3	digital 6	PD6	AIO3	analog 2	PC2
P4	DIO4	digital 7	PD7	AIO4	analog 3	PC3

